

Configure MB6000 for T-Mobile networks

1. Go to the webGUI of MB6000 (3G Phoebus)->Interfaces->Internet access:

Interfaces: Internet access

Enable this interface Check this box.

Interface type: Wireless Internet access

Connect mode:
• Auto: Automatically dial up when power up.
 • Dial on-demand: Dial up when LAN data request to access Internet.
 • Manual: Manually dial up by client software or from web page.(see the [Status:Interface page](#))

DNS: Obtain DNS server address automatically Check this box.
 DNS Server:

Keepalive: Enable keepalive
 seconds
 Reset Modem After redialing
 Reboot System After resetting Modem

Username:

Password: Leave them empty.

Hardware

Card model: GLOBE TROTTER HSDPA /GPRS Card

Singal strength: Invalid (0) **Hint:** Good:31-24,Normal:23-16,Poor:15-8,Bad:7-1,Invalid:0

Modem:

Phone number	<input type="text" value="*99***1#"/>
CID	<input type="text" value="1"/>
PDP Type	<input type="text" value="ip"/>
APN	<input type="text" value="internet3.voicestream.com"/>
PDP Address	<input type="text" value="0.0.0.0"/>
Data Compress	<input type="text" value="0"/>
Header Compress	<input type="text" value="0"/>

2. Check the check box of “*Enable this interface*” to enable the 3G Data card, and leave the username and password fields blank.

3. Check “*Obtain DNS server address automatically*”.

4. Make sure you have correctly input the parameters as below:

- Dial number: *99***1# or *99#
- APN: internet3.voicestream.com

5. Leave all the other parameters as the default value then submit the configurations.

6. Click “*Commit*” button and follow the instruction to reboot the MB6000 then MB6000 will dial up automatically.



TOP Global Technology Ltd.

ADDR: 4605 Barranca Parkway Suite 101G

Irvine, CA 92604

TEL: +1-949-586-7046

FAX: +1-949-586-8299

<http://www.topglobalusa.com/>
